

Compact parallel grippers with T-guide Series CGSP



Single and double acting, magnetic, self-centering

Sizes: 20, 25, 32, 40









Series CGSP grippers, available in 4 sizes (20, 25, 32 and 40) are parallel and double acting, self-centering and guided by means of a T-shaped sliding guide. Thanks to the materials and surface coating used, the gripper offers a high reliability. Moreover, the internal force transmission system is protected against the entrance of impurities by means of a steel cover so the gripper can also be used in dusty environments.

Extreme compact dimensions, a light design and high positioning repeatability make this series of grippers particularly suitable for handling small items, even if high operating frequencies are required. Typical applications are pick & place, insertion, machine tending in the electronic components assembly sector, cosmetics & medical industry or in food packaging.

- » Robust, compact and light design
- » High resistance to external loads thanks to the T-guide
- » High closing/opening repeatability
- » High reliability
- » Position detection thanks to magnetic proximity switch or inductive sensor kits.
- » Protected against the entrance of impurities (IP40)
- » Free from Copper, Silicone and PTFE
- » High interchangeability (centering bushes)
- » Variants available for use in ATEX zones

GENERAL DATA

Type of construction Self-centering parallel gripper with T-guide Operation Single acting (NO, NC), double acting

Ø20, 25, 32, 40 mm Bores

Force transmission

M3 (Ø20, 25), M5 (Ø32, 40) Air connections

Working temperature 5°C ÷ 60°C Storage temperature -10°C ÷ 80°C

Maximum use frequency 3 Hz (Ø20, 25, 32), 2 Hz (Ø 40)

Repeatability 0.02 mm Interchangeability

Medium Filtered air in class 7.4.4 according to ISO 8573-1. In case lubricated air is used, we recommend ISOVG32 oil and to never interrupt

lubrication

Lubrication After 10 million cycles, grease the sliding zones using Molykote DX grease

Protection class

Compatibility **ROHS** Directive

Certifications ATEX (II 2GD c IIC 120°C(T4)-20°C≤Ta≤80) Materials PTFE, Silicone and Copper free

Working pressure Double acting: 2 ÷ 8 bar Single acting: 4 ÷ 8 bar

N.B. Pressurize the pneumatic system gradually in order to avoid uncontrolled movements



CODING EXAMPLE

CGSP	-	20	-	NC NC	-	EX
CGSP	SERIES					
20	SIZES 20 25 32 40					
NC	FUNCTIONING = double acting NO = single acting, norn NC = single acting, norn			PNEUMATIC SYMBOI PNZ1 PNZ3 PNZ2	LS	
EX	CERTIFICATION = standard EX = ATEX certification					

PNEUMATIC SYMBOLS

The pneumatic symbols which have been indicated in the CODING EXAMPLE are shown below.










Series CGSP grippers - construction



LIST OF COMPONENTS		
PARTS	MATERIALS	
1 - Body	Aluminium	
2 - End cap	Aluminium	
3 - End cap NC/NO	Aluminium	
4 - Piston	Stainless steel	
5 - Jaw	Stainless steel	
6 - Levers	Steel	
7 - Cover	Stainless steel	
8 - Spring	Stainless steel	
9 - End cover	Aluminium	
10 - Centering bushes	Stainless steel	
11 - Seals	HNBR / FKM	
12 - Magnet	Neodymium	
13 - Screws and grub screws	Stainless steel	
14 - Pins	Steel	

C₹ CAMOZZI

CGSP gripper, size 20 - dimensions




- DRAWING LEGEND:


 A = Opening of air connection


 B = Closing of air connection


 C = Closed gripper


 D = Open gripper











Mod.	Total closing gripping force at 6 bar (N)	Closing gripping force each jaw at 6 bar (N)	Total opening gripping force at 6 bar (N)	Opening gripping force each jaw at 6 bar (N)		Working pressure (bar)	Working temperature (°C)	Opening time (ms)	Closing time (ms)	Weight (g)
CGSP-20	36	18	44	22	2	2 ÷ 8	5 ÷ 60	9	12	34
CGSP-20-NC	46	23	38	19	2	4 ÷ 8	5 ÷ 60	9	10	42
CGSP-20-NO	30	15	54	27	2	4 ÷ 8	5 ÷ 60	12	7	40





CGSP gripper, size 25 - dimensions





- A = Opening of air connection
 B = Closing of air connection
 C = Closed gripper


- D = Open gripper












Mod.	Total closing gripping force at 6 bar (N)	Closing gripping force each jaw at 6 bar (N)	Total opening gripping force at 6 bar (N)	Opening gripping force each jaw at 6 bar (N)		Working pressure (bar)	Working temperature (°C)	Opening time (ms)	Closing time (ms)	Weight (g)
CGSP-25	70	35	84	42	3	2 ÷ 8	5 ÷ 60	11	13	51
CGSP-25-NC	86	43	76	38	3	4 ÷ 8	5 ÷ 60	9	24	66
CGSP-25-NO	62	31	98	49	3	4 ÷ 8	5 ÷ 60	20	8	61


C₹ CAMOZZI


CGSP gripper, size 32 - dimensions





- A = Opening of air connection
 B = Closing of air connection
 C = Closed gripper











Mod.	Total closing gripping force at 6 bar (N)	Closing gripping force each jaw at 6 bar (N)	Total opening gripping force at 6 bar (N)			Working pressure (bar)	Working temperature (°C)	Opening time (ms)	Closing time (ms)	Weight (g)
CGSP-32	104	52	122	61	4	2 ÷ 8	5 ÷ 60	18	20	99
CGSP-32-NC	126	63	106	53	4	4 ÷ 8	5 ÷ 60	9	27	126
CGSP-32-NO	88	44	142	71	4	4 ÷ 8	5 ÷ 60	22	8	120





CGSP gripper, size 40 - dimensions





- A = Opening of air connection
 B = Closing of air connection
 C = Closed gripper


- D = Open gripper












Mod.	Total closing gripping force at 6 bar (N)	Closing gripping force each jaw at 6 bar (N)	Total opening gripping force at 6 bar (N)	Opening gripping force each jaw at 6 bar (N)		Working pressure (bar)	Working temperature (°C)	Opening time (ms)	Closing time (ms)	Weight (g)
CGSP-40	154	77	184	92	6	2 ÷ 8	5 ÷ 60	16	13	163
CGSP-40-NC	188	94	152	76	6	4 ÷ 8	5 ÷ 60	11	28	238
CGSP-40-NO	124	62	214	107	6	4 ÷ 8	5 ÷ 60	27	11	219

CAMOZZI Automation

GRIPPING FORCE PER SINGLE JAW




L = distance from gripping point

FA = opening force

FC = closing force

FAM = opening force of the spring


FCM = closing force of the spring



CGSP-20



GRIPPING FORCE PER SINGLE JAW




CGSP-25

L = distance from gripping point FA = opening force FC = closing force


FAM = opening force of the spring


FCM = closing force of the spring



CAMOZZI Automation

GRIPPING FORCE PER SINGLE JAW






CGSP-32

L = distance from gripping point FA = opening force FC = closing force


FAM = opening force of the spring

FCM = closing force of the spring





GRIPPING FORCE PER SINGLE JAW




<u>≥</u> 90 80 70 60 50 40 4Bar 30 4Bar 20 10 0 0 0,02 0,04 0,06 0,08 L (mm)

CGSP-40

L = distance from gripping point FA = opening force FC = closing force


FAM = opening force of the spring


FCM = closing force of the spring




CAMOZZI Automation

Examples of mounting








Mod.	А	В	С	D	E	F
CGSP-20	Ø4	M2.5	M2.5	Ø1.5	M4	Ø1.5
CGSP-25	Ø5	M3	М3	Ø2	M4	Ø1.5
CGSP-32	Ø6	M4	M3	Ø2	M5	Ø2
CGSP-40	Ø6	M4	M3	Ø2.5	M5	Ø2.5



Air supply ports




Mod.	G	Н	I
CGSP-20	М3	-	-
CGSP-25	М3	M2	OR 1x2.5
CGSP-32	M5	M2.5	OR 1x3
CGSP-40	M5	M3	OR 1x3.5

Magnetic sensors fixing kit



- Supplied with:
- fixing screws (M) flange (L)




Mod.	М	N
M-CGSP-20	M2x6	CSD
M-CGSP-25	M2x6	CSD
M-CGSP-32	M2x6	CSD
M-CGSP-40	M2x6	CSD

Inductive sensors fixing kit



- Supplied with:
- fixing screws (S)
- setting screws (Q R) flange (P)



Mod.	Q	R	S	T
I-CGSP-20	M1,6x3	M1,6x6	M2x6	Ø3
I-CGSP-25	M2x4	M2x8	M2x8	Ø4
I-CGSP-32	M2x4	M2x8	M2x8	Ø4
I-CGSP-40	M2x4	M2x10	M2x10	Ø4




Series CSD magnetic proximity switches, 3-wire cable, D-slot











Mod.	Operation	Connections	Voltage	Output	Max. current	Max Load	Protection	L = length cable
CSD-D-334	Magnetoresistive	3 wires	10 ÷ 27 V DC	PNP	200 mA	6W	Against polarity reversing and overvoltage	2 m

Series CSD magnetic switches, male M8 3-pin conn., D-slot, right

Length of cable 0.3 metres







Mod.	Operation	Connection	Voltage	Output	Max. current	Maxload	Protection
CSD-D-364	Magnetoresistive	3 wires with M8 connector	10 ÷ 27 V DC	PNP	200 mA	6W	Against polarity reversing and overvoltage